GIGAMEDIA
SMART BUILDING SOLUTIONS

Mixer amplifier 5 zones with pre-recorded message 480W
GGM PAM5480R



The multi-zone mixer amplifier has 5 distinct zones with adjustable volume, high and low notes for each of the zones. It has a local microphone input, an auxiliary line input and two inputs for remote microphone connections. It is possible to record a signal from an auxiliary line input or to diffuse via an input in short-circuit a message (for example, evacuation order, warning, etc.) pre-recorded in a memory built into the product. Each zone can be supervised for breakdown detection. This product can integrate an MP3 reader on a USB port or SD card. Possibility to connect up to 5 PAM 5MIC per amplifier.

Article features

- Auxiliary input : Asymmetric RCA
- Speaker output : 100v
- Microphone input : Yes
- Mixed output : Unbalanced rca auxiliary
- Mp3 player (usb and sd card) : Yes
- Number of areas : 5
- Output power : 480w
- Rack mountable : 3u
- Total power (w) : 650
- Triggering of a pre-recorded message on contact se : Yes
- Weight (kg) : 8

ETIM 10 features

- Model : Mixing amplifier
- Freestanding : Yes
- Rack-assembly possible : Yes
- 70 V amplifier : No
- 100 V amplifier : Yes
- Music power at 100 V : 480 W
- Inputs with priority switching : Yes
- Number of analogue inputs : 3
- Number of analogue outputs : 1
- Number of loudspeaker outputs : 5
- Number of RCA audio sockets : 2
- Number of supported paging zones : 5
- Number of microphone inputs : 2
- With display : No
- With VU meter : Yes
- With remote control : Yes
- Operation by app : No
- Handling with software : No
- With backup battery : No
- Colour : Black
- Material : Metal
- Width : 484 mm
- Height : 88 mm
- Depth : 375 mm