



## BREAK ELECTRIC STRIKE PLATE

### GGM AXERC1L



#### STRIKE RUPTURE + TET SYM LONG

The GGM AXEE0A1L is a recessed breakaway electric strike working in fail-safe mode (normally closed). It is a reversible, symmetrical product and uses a 12 V DC supply. It is delivered with a long faceplate suitable for most projects.

#### FEATURES

<b>Strike type :</b>	Fail safe
<b>Operating mode :</b>	Rupture
<b>Retention force (kg) :</b>	500
<b>Power supply :</b>	12 vdc
<b>Operating temperature range :</b>	From -10°C to 55°C
<b>Headrest :</b>	Long
<b>Voltage (V) :</b>	12
<b>Power Consumption :</b>	200 mA
<b>Integrated varistor :</b>	No
<b>Material :</b>	Stainless steel
<b>Format :</b>	Symmetrical
<b>Built-in position :</b>	Universal
<b>Height :</b>	250 mm
<b>Width :</b>	25 mm
<b>Depth :</b>	28 mm
<b>Assembly arrangement :</b>	Frame part

<b>With adjustment :</b>	No
<b>With mechanical unlocking :</b>	No
<b>With feedback signal :</b>	No
<b>Opening direction (according to DIN) :</b>	Left/right
<b>Water protected :</b>	No
<b>Mounting method :</b>	Built-in
<b>Compatible with Apple HomeKit :</b>	No
<b>Compatible with Google Assistant :</b>	No
<b>Type of current :</b>	DC
<b>Principle of operation :</b>	Working current
<b>Compatible with Amazon Alexa :</b>	No
<b>IFTTT support available :</b>	No
<b>Pulse contact :</b>	No
<b>Adjustable door opener latch :</b>	No
<b>Adjustable door opener :</b>	No
<b>Adjustable strike plate :</b>	No
<b>Latch guide integrated :</b>	No
<b>For latch bolt slide :</b>	No
<b>Unlocking method :</b>	Standard model
<b>Continuous operation (100 % ED) :</b>	No
<b>Mechanical unlock :</b>	No
<b>Suitable for fire protection door :</b>	No
<b>Suitable for smoke protection door :</b>	No
<b>Forend shape :</b>	None
<b>With strike plate :</b>	Yes
<b>Basic colour of strike plate :</b>	Silver
<b>Length of strike plate :</b>	90 mm
<b>Width of strike plate :</b>	25 mm
<b>Deadbolt output :</b>	Yes
<b>For bolt switch contact prepared :</b>	No

PART-NUMBER	DESCRIPTION
GGM AXERC1L	STRIKE RUPTURE + TET SYM LONG