



## 6 zone pulpit microphone for PAM6120S3 and PAM6240S3 GGM PAM6MIC



The GGM PAM6MIC is a pulpit microphone which is able to manage the 6 zones of the GGM PAM6120S3 and PAM6240S3. It offers the possibility to manage in either an overall manner or separately each zone to diffuse your message. It is possible to connect up to 6 pulpits in cascade thanks to the RS485 port (input and output) and to choose the 2-4 tone chime before diffusion of the message.

### Article features

- Built-in chime : 2-4 tones
- Max link distance (km) : 1
- Number of areas : 6
- Remote microphone link : Rs485
- Sensitivity : 10 mv
- Supply voltage : 24 vdc - 500 ma
- Type of microphone : Static
- Weight (kg) : 1

### ETIM 10 features

- With gooseneck : Yes
- Stereo : No
- Wireless : No
- Watertight : No
- With LCD indication : No
- With lock function : No
- With wind protection : No