



4 zone pulpit microphone for PAX4120S2 GGM PAX4MIC



The GGM PAX4MIC is a pulpit microphone which is able to manage the 4 zones of the GGM PAX4120S2. It offers the possibility to manage in either an overall manner or separately each zone to diffuse your message. It is possible to connect up to 6 pulpits in cascade thanks to the RS485 port (input and output) and to choose the 2-4 tone chime before diffusion of the message.

Article features

- Built-in chime : 2-4 tones
- Power Consumption : 10w
- Max link distance (km) : 1
- Number of areas : 4
- Output voltage (V) : 1v - 600Ohm
- Remote microphone link : Rs485
- Supply voltage : 24 vdc - 500 ma
- Type of microphone : Static
- Weight (kg) : 0.96

ETIM 10 features

- With gooseneck : Yes
- Stereo : No
- Wireless : No
- Sensitivity : -47 dB
- Watertight : No
- With LCD indication : No
- With lock function : No
- With wind protection : No